



DXA – IP ADDRESS SETTINGS

Tech note TN12xxx

- ❖ This tech note explains how to configure the DX Advanced IP address settings. You will enter the basics settings mode of the recorder and the Ethernet communication functions to configure these settings.
- ❖ Refer to the main User Manual for your DX model for more information on all functions and settings.

❖ 1. Go to Basic Setting mode

❖ Press MENU key

- Hold FUNC key for 3 seconds
- Select Menu tab
- Using down arrow key, select Communication (Ethernet)
- Press right arrow key to display setting menu
- Using up/down arrow keys select (IP-Address, Host settings)

❖ 2. IP Address, Host settings

- ❖ Under **IP Address, Host settings** menu you will configure the recorders IP Address settings.
 - Select **use/not** for DHCP depending on if the IP Address is a static or fixed address.
 - For fixed IP Address enter the IP address and Subnet mask under fixed IP address settings.
 - **NOTE:** The IP address should match the IP address of the PC with the exception of the last numerical digit. See example on next page.

❖ 2. IP Address, Host settings

EXAMPLE:

- PC IP Address: 192.168.10.1
- DX IP Address: 192.168.10.2
- Press the Disp/Enter key to save the settings
- Press ESC key 3 times.
- Box will appear asking if you want to store and make the new settings take effect.
- Select YES. Recorder will re-boot.
- DONE.....



Thank you!