



YS1700 – Initializing to Factory Defaults

Tech note TN12015

- ❖ This tech note makes it possible to revert the YS1700 back to the factory default condition.
- ❖ This is sometimes necessary when unknown changes have been made to the program/configuration causing problems with the particular process.



WARNING: Do not explore any of the other menus/parameters not outlined in this procedure. Making changes not described here can cause your controller to cease to function properly. This problem will not be covered under warranty.





❖ Initializing the YS1700 cont.

1. Apply power to the controller while pressing the

 key and  key simultaneously.

2. Use the soft keys ,  to highlight “TEST” then press the soft keys , , to set the password 5678.

3. Press the  key **2 times** while holding the  key to show the ADJ MENU.

❖ Initializing the YS1700 cont.

4. Select “CALIB 1” using the soft keys.

5. Use the soft keys ,  to highlight “PINIT” then press the soft keys , , to set the value to 1.

6. The value will automatically return to 0 within five seconds. Leave the unit undisturbed for 15 seconds.

7. Cycle power. Initialization Complete.



Thank you!